

# Instructions – Radio Hand-Held Transmitter

Enables the control of wireless roller shutter motors – conveniently and without cables.



Nominal voltage:	2 x 1.5 VDC
Transmission frequency:	433.92 MHz
Transmission power:	10 mW
Number of channels:	1
Operating temperature:	-10 °C to +70 °C
Battery type:	AAA
Display:	LED display (function display only)
Fastening:	Wall bracket with screws (2 pcs. 3x16 mm)
Scope of supply:	Radio Hand-Held Transmitter, wall bracket, 2x AAA battery, screws
Dimensions:	143 x 40 x 22 mm

Product name	PU	Item no.
blaugelb Radio Hand-Held Transmitter	1 piece	9084801

## Note:



The programming, which usually consists of a combination of buttons, must be carried out within 10 seconds. The application is intended for dry environments (IP54).

To change the battery, slide the cover on the back down and insert the two AAA 1.5 V batteries according to the polarity.

The wall bracket included in the scope of supply can be attached with the enclosed mounting material. The hand-held transmitter is held magnetically in the holder.

## Programming:

Back of the blaugelb Radio Hand-Held Transmitter:



Before the blaugelb Radio Hand-Held Transmitter can be used, it must be coupled once with the respective motor.

Action		Execution and comment
01	<b>P1</b>	Press button briefly, drive beeps and turns
02	<b>P2</b>	Press button briefly, drive beeps and turns
03	<b>P2</b>	Press button briefly again, drive beeps and turns
04	<b>▲</b>	Press UP button, drive beeps and turns
05		<b>Programming completed</b>
If the motor is running in the wrong direction		
01	<b>P1</b>	Press button for approx. 5 seconds, drive beeps and turns
02		<b>Direction of rotation changed</b>

## Decoupling the transmitter:

Action		Execution and comment
01	<b>P2</b>	Press button, drive beeps and turns
02	<b>■</b>	Press Stop button, drive beeps and turns
03	<b>P2</b>	Press button again, drive beeps and turns
04		<b>Transmitter is decoupled</b>

## Teaching an additional transmitter:

(Here, several transmitters can be assigned to one roller shutter motor or a group of roller shutter motors so that they can function as equal operating elements)

Action		Execution and comment
<b>On the already taught transmitter</b>		
01	<b>P2</b>	Press button, roller shutter motor beeps and turns
02	<b>P2</b>	Press button, roller shutter motor beeps and turns
<b>On the new transmitter to be taught</b>		
03	<b>P2</b>	Press button again, roller shutter motor beeps and turns
04		<b>Teaching process is completed</b>